

### Mixing Amplifier with Zone **EMMA-825ZSMKII / EMMA-835ZSMKII**



EMIX EMMA-8ZS Series mixing amplifiers have two ranges of power ratings: 250W and 350W. The mixing amplifier is integrated with a USB player for MP3 playback. It is design with both high (100V) and low (4-16Ω) impedance speaker system. The LED output meter is to monitor the output signal level.

It is standard 19" rack mountable with ear piece provided and only takes up 2U of space.

#### FEATURES

- 250W and 350W, 100V Line & 4-16Ω
- 4 Mic inputs, 3 AUX input, 1 Line output
- Phantom power for Mic 3 and 4
- USB / SD card player and FM Tuner
- Built in chime for announcement
- 6 zones individual output volume control
- Bass and Treble control
- LED as output level meter
- Short circuit, overload and high temperature protection

#### SPECIFICATIONS

	EMMA-825ZSMKII	EMMA-835ZSMKII
Rated Output	250W	350W
Output Regulation	Less than 3dB, from no load to full load	
Speaker Output	Balanced, 4-16Ω and 70V, 100V	
Input Sensitivity	MIC: 3mV (±0.5mV), LINE: 300mV (±50mV)	
Frequency Response	80Hz – 16kHz (±3dB)	
Distortion	Less than 1% (at 1kHz, 1/3 rated output voltage)	
S/N Ratio	MIC: more than 71dB, LINE: more than 85dB	
Tone	Bass : ±12dB at 100Hz Treble : ±12dB at 10kHz	
Protection	AC Fuse, DC Fuse, Overload, Short Circuit, Temperature	
Power Supply	AC 240V/50Hz	
Power Consumption	500W	650W
Dimension (W x H x D)	485 x 88 x 338mm (2U)	
Net Weight	14kg	17kg
Gross Weight	16kg	19kg

#### REAR VIEW

