Power Amplifier EMPA-8250 / EMPA-8380 / EMPA-8500



DESCRIPTION

EMIX EMPA-8250 is a 100V line power amplifier with rated output of 250W, EMPA-8380 with 380W and EMPA-8500 with a very powerful 500W output.


All EMIX power amplifiers are equipped with automatic self-resetting thermal cut off in the event unusual heat build-up in the unit. It has built-in shirt circuit protection. This EMPA series amplifier is capable of handling a wide variety of public address requirements at a surprising performance.

It is standard 19" rack-mountable with earpiece provided and only takes up to 2U of space.

FEATURES

- Transformer isolated 100V, 70V and 8Ω speaker outputs, balanced, no grounding
- 6 LED output signal indicator
- · XLR connector for amplifier link
- Short circuit, thermal, overload protection with LED indication
- · Complete with priority input
- Supports 100V line input
- · Input gain control available located behind amplifier

SCHEMATIC DIAGRAM



SPECIFICATIONS

| Model | EMPA-8250 | - 1 | EMPA-8380 | 1 | EMPA-8500 |
|-----------------------|---|-----|-------------|---|-------------|
| Rated Power | 250W RMS | | 380W RMS | | 500W RMS |
| Input Sensitivity | 1V | | | | |
| S/N Ratio | > 90dB | | | | |
| Frequency Response | 80Hz – 16kHz at ± 3dB | | | | |
| THD (4Ω/1kHz) | < 0.5% | | | | |
| Cooling Style | 12V DC Fan | | | | |
| Indicators | Power, Clip, Temperature, Protection | | | | |
| Protection | Turn on delay, Thermal, DC fault, short circuit | | | | |
| 240V AC Fuse | F6AL | | F8AL | | F10AL |
| 24V DC Fuse | FB15AL / FC10AL | | FB/FC: 15AL | | FB/FC: 20AL |
| Power Supply | AC 220-240 / 50-60Hz or 24V DC | | | | |
| Power Consumption | 500W | - 1 | 760W | | 1000W |
| Dimension (W × H × D) | 483 × 88 × 390mm (2U) | | | | |
| Gross Weight | 17kg | | 19.3kg | | 20.6kg |
| Net Weight | 16kg | I | 18.3kg | | 19.5kg |

