

# EMRM-812 Monitor Unit



The **EMIX** EMRM-812 provides the convenience of monitoring up to 10 power amplifier outputs. It allows the selection of any 1 of 10 power amplifiers to be monitored. It is designed specifically for 100V line distributed speaker systems.

Visual indication is provided by a 5 segments LED level meter. This LED meter accurately indicates the output level of the power amplifiers.

The EMRM-812 also provides audio monitoring via a high quality 5cm dynamic full range loudspeaker built into the unit.

It is standard 19" rack-mountable with earpieces provided and only takes up 2U of space.

## Features

- > Convenient monitoring up to 10 power amplifier outputs
- > 5 segments LED level meter provided for visual monitoring
- > 5cm dynamic full range loudspeaker unit with built-in attenuator for audio monitoring of the selected amplifier output.

Model	EMRM-812
Channels	10, switchable
Inputs	70V-100V, 10k Ohms
Output	SPL 65dB, Variable
Frequency Response	100Hz-15kHz
Signal to Noise Ratio	80dB
Speaker	Built-in internally
Protection	AC fuse
Power Supply	240VAC $\pm$ 10%, 50/60Hz or DC24V $\pm$ 10%
Dimensions (W x H x D)	485 x 88 x 365mm
Gross Weight	6.5kg
Net Weight	5.2kg

## Rear View



## Schematic Diagram

