



MA-250

MIXING AMPLIFIER WITH BUILT IN USB, FM & BLUETOOTH PLAYER



High Power mixer amplifier with USB/FM and Bluetooth. The Speaker output is 70V/100V.is the new cost-effective and stable mixer amplifier solution.



FEATURES:

- Built in USB, FM and Bluetooth
- 6 Zones Output with Individual Volume Control
- 2 microphone input and 3 AUX input
- AUX output
- Suitable for high or low impedance speaker
- Running on AC 240V
- Treble / Bass Control
- Over Current, Short Circuit Protection

SPECIFICATIONS

OUTPUT POWER	250W
OUTPUT TYPE	70V / 100V / 4~16Ω
MIC INPUT	3mV, 600Ω
LINE INPUT	200mV, 10kΩ
FREQ. RANGE	40Hz ~ 20kHz
DISTORTION	0.5% (1kHz)
S/N RATIO	AUX: 88 dB MIC: 116 dB
VOLTAGE	110V / 220V
DIMENSION	480 * 370 * 88 mm (2U)