

TA-8008
AM/FM Tuner



TA-8008 Tuner

The AM/FM Radio Tuner have microcomputer controlled MPU synthesized circuit and a VFD display to indicate the receiving frequency and output level meter. Radio station frequencies can be searched automatically or manually. AM and FM frequencies can be preset up to 40 memories. All preset memory shall not be erased even after power failure.

Features:

- » Microprocessor based control, digital tuning system
- » Soft touch button, VFD display
- » Radio station auto scan & memorize function are provided, includes 40 memories
- » Auto saves with auto station search
- » Resume memory state after power failure, volume LED indicator
- » Network PC control and timer

Technical Specifications

TA-8008 Tuner		
Band	FM	87.0 ~ 108.0 MHz
	AM	522 ~ 1620 kHz
Sensitivity	FM	18 dBμ
	AM	52 dBμ
S/N	FM	Mono 76 dB, Stereo 70 dB
	AM	40 dB
Freq. Step	FM	50 kHz
	AM	9 kHz
MF	FM	10.7 MHz
	AM	450 kHz
Output level	0 dBV	
Protection	AC fuse x 1	
Power Requirement	1. AC 230V/50~60 Hz	
	2. DC 24V	
Dimensions	485 x 88 x 345 mm	
Net Weight	5.4 kg	

* Specifications are subject to change without prior notice