

**FEATURES:**

- Built in USB, FM and Bluetooth
- 2 Zones Output with Individual Volume Control
- 2 microphone input and 1 AUX input
- AUX output
- Suitable for high or low impedance speaker
- Running on AC 240V
- Treble / Bass Control
- Over Current, Short Circuit Protection

Designed 1.5U mixer amplifier with USB/FM and Bluetooth. The Speaker output is 70V/100V is the new cost-effective and stable mixer amplifier solution.

**SPECIFICATIONS**

Rated power	120W
Output mode	4–16Ω, 70V / 100V
Frequency response	35Hz – 20kHz ±2dB
Microphone Input	600Ω – 52dB
Recording Output Level	600Ω – 0dB (–10dB)
Line Output	±40dB
Voltage	220V ±10% 50Hz
Dimension	482 × 275 × 68mm