

#### **TA-8017** Digital Message Program Player



## TA-8017 Digital Message Program Player

The Digital Message Program Player is able to play music files as well as pre-recorded messages. It is able to store and play multiple messages or total 45 minutes of messages. The LCD with backlight display provides clear information about the status of the unit and also error notifications. A jog-Dial Control is provided with graphic interfaces and multi-level menu for use of adjustment. The unit is 19" rack mountable. The program player is provided 2 record MIC inputs, 1 record input and dual stereo output. The playback of pre-recorded files with controlled and scheduled by connecting the unit to the programmable timer via data link port.

#### **Features:**

- » Microprocessor chip control, soft touch button
- » Shuttle/jog button, direct select program
- » PC Remote control or timer control
- » LCD display, Chinese menu
- » 2 Mic input, 1 line input, 2 way output
- » Network PC control

## Technical Specifications

TA-8017 Digital Message Recorder	
Record Input	Mic in : 600Ω , 2.5 mV, unbalance Line in : 10 kΩ, 250 mV, unbalance
Output	600Ω, 0dB
Record Frequency	100 Hz - 4 kHz
Signal to Noise	Mic input : 65 dB Aux input : 75 dB
Maximum Memory Capacity	45 minutes
Protection	AC fuse x 1 A
Power Requirement	AC 230V/110V/ 50~60Hz
Dimensions	485 x 88 x 375 mm
Gross Weight	8.5 kg
Net Weight	7.0 kg