

MINI MIXER (*balanced*)

TA-0073



The TechAudio TA-0073 are used in mixing 2 Balanced audio signal with individual gain adjustment,. This unit is extremely useful when ad-hoc when mixing balanced/unbalanced audio signal is needed

TECHNICAL SPECIFICATIONS

Input Voltage	24V DC
Frequency Response	-3dB (20Hz to 20KHz)
Max. Gain	+8.0dB
Min. Gain	-1.1dB
Input Impedance	20K Ohm Unbalanced 40K Ohm Balanced
Maximum Input	1.6V RMS Unbalanced 3.2V RMS Balanced
Maximum Output	4.6V RMS Unbalanced 9.4V RMS Balanced
Dimension (W X H X D)	135mm X 8.5mm X 2.5mm (w/o bracket)
Weight	400gm

Note: The specifications are subject to change without prior notice.